

Conversion from Nordac Vector MC to Nordac SK500E

1 phase 230V supply (for 3 phase 230V output to the motor)

Vector MC				
Motor Power	Type Code	Part number		Dimensions
				H x W x D (mm)
0.25kW	SK 250/1 FCT	278002500	Size 1	154x86x134
0.37kW	SK 370/1 FCT	278003700	Size 1	154x86x134
0.55kW	SK 550/1 FCT	278005500	Size 1	154x86x134
0.75kW	SK 750/1 FCT	278007500	Size 1	154x86x134
1.1kW	SK 1100/1 FCT	278011000	Size 2	191x112x135
1.5kW	SK 1500/1 FCT	278015000	Size 2	191x112x135
2.2kW	SK 2200/1 FCT	278022000	Size 2	191x112x135

>

>

>

>

>

>

>

SK500E				
Motor Power	Type Code	Part number		Dimensions
				H x W x D (mm)
0.25kW	SK 500E-250-323-A	275410025	Size 1	186x74x153
0.37kW	SK 500E-370-323-A	275410037	Size 1	186x74x153
0.55kW	SK 500E-550-323-A	275410055	Size 1	186x74x153
0.75kW	SK 500E-750-323-A	275410075	Size 1	186x74x153
1.1kW	SK 500E-111-323-A	275410110	Size 2	226x74x153
1.5kW	SK 500E-151-323-A	275410150	Size 2	226x74x153
2.2kW	SK 500E-221-323-A	275410220	Size 2	226x74x153

3 phase 400V supply (for 3 phase 400V output to the motor)

Vector MC				
Motor Power	Type Code	Part number		Dimensions
				H x W x D (mm)
0.75kW	SK 750/3 FCT	278007550	Size 2	191x112x135
1.1kW	SK 1100/3 FCT	278011050	Size 2	191x112x135
1.5kW	SK 1500/3 FCT	278015050	Size 2	191x112x135
2.2kW	SK 2200/3 FCT	278022050	Size 2	191x112x135
3kW	SK 3000/3 FCT	278030050	Size 2	191x112x135

>

>

>

>

>

>

SK500E				
Motor Power	Type Code	Part number		Dimensions
				H x W x D (mm)
0.75kW	SK 500E-750-340-A	275420075	Size 1	186x74x153
1.1kW	SK 500E-111-340-A	275420110	Size 2	226x74x153
1.5kW	SK 500E-151-340-A	275420150	Size 2	226x74x153
2.2kW	SK 500E-221-340-A	275420220	Size 2	226x74x153
3kW	SK 500E-301-340-A	275420300	Size 3	241x98x178

Options

Vector MC		
Type Code	Part number	Description
Controlbox MC	278900000	7 segment box
PROFIBUS MC	278900060	Profibus field bus option
CANopen MC	278900080	CANopen field bus option
Devicenet MC	278900090	Devicenet field bus option

>

>

>


>

SK500E		
Type Code	Part number	Description
SK TU3-CTR	275900090	7 segment Control box for programming and display
SK TU3-PBR	275900030	Profibus field bus option
SK TU3-CAO	275900075	CANopen field bus option
SK TU3-DEV	275900085	Devicenet field bus option

For any other options contact Nord UK

Conversion from Nordac Vector MC to Nordac SK500E


Vector MC Dimensions




Inverter type	Length "L1"	Width "W1"	Depth "D"	Detail: Attachment rail		
				Length "L2"	Hole spacing "L3"	"a"
SK 250/1 FCT to SK 750/1 FCT	154	86	134	184	177	15
SK 1100/1 FCT to SK 2200/1 FCT	191	112	135	221	213,5	15
SK 750/3 FCT to SK 3000/3 FCT						

Conversion from Nordac Vector MC to Nordac SK500E


SK500E Dimensions



Device type	Size	Housing dimensions			Wall mount (chap. 2.3)	
		A	B	C	D, approx.	Ø
SK 5xxE-250- ... SK 5xxE-750- ...	BG1	186	74 *	153	220	5.5
SK 5xxE-111- ... SK 5xxE-221- ...	BG2	226	74 *	153	260	5.5
SK 5xxE-301- ... SK 5xxE-401- ...	BG3	241	98	178	275	5.5




Conversion from Nordac Vector MC to Nordac SK500E





Conversion from Nordac Vector MC to Nordac SK500E

Vector MC



VectorMC		SK500E	
Pin	Function	Terminal	Pin
1	Relay Output 1	X3	1
2	Relay Output 1	X3	2
3	Relay Output 2	X3	3
4	Relay Output 2	X3	4
5	+10V Supply	X4	11
6	0V	X4	12
7	Analog Common	X4	12
8	Analog Input +	X4	14
9	Analog Output	X4	17
10	Digital Input 1	X5	21
11	Digital Input 2	X5	22
12	Digital Input 3	X5	23
13	Digital Input 4	X5	24
14	+15V Supply	X5	42
15	+5V	RJ12 PLUG	6
16	0V	RJ12 PLUG	3
17	P + RS485	RJ12 PLUG	1
18	N - RS485	RJ12 PLUG	2

SK500E



Vector MC